

Electrical Data:

| Model | Electrical Data | | | | | |
|--------|------------------|---------------|---------------|------|-----------|----------------------|
| | Voltage 60 Hz | kW Maximum | hp Nominal | S.F. | I Amps | Capacitor μ F |
| JPF2A | 115 | 0.65 | 1/3 | 1.75 | 6 | 40 |
| JPF2A | 230 | 0.65 | 1/3 | 1.75 | 3 | 10 |
| JPF3A | 115 | 0.85 | 1/2 | 1.6 | 7.5 | 20 |
| JPF3A | 230 | 0.85 | 1/2 | 1.6 | 3.8 | 12.5 |
| JPF4A | 115 | 1.10 | 3/4 | 1.5 | 10 | 64 |
| JPF4A | 230 | 1.10 | 3/4 | 1.5 | 5 | 16 |
| JPF41A | 115 | 1.31 | 1 | 1.4 | 12 | 80 |
| JPF41A | 230 | 1.31 | 1 | 1.4 | 6 | 20 |
| JPF5A | 230 | 1.70 | 1.5 | 1.3 | 8 | 31.5 |
| JPF7A | 230 | 2.40 | 2 | 1.2 | 11 | 40 |
| JPS2A | 115 | 0.88 | 1/2 | 1.6 | 7.6 | 50 |
| JPS2A | 230 | 0.82 | 1/2 | 1.6 | 3.7 | 12.5 |
| JPS4A | 115 | 1.6 | 1 | 1.4 | 13.6 | 80 |
| JPS4A | 230 | 1.53 | 1 | 1.4 | 7 | 20 |
| JDF2A | 115 | 0.75 | 1/2 | 1.6 | 7 | 50 |
| JDF2A | 230 | 0.75 | 1/2 | 1.6 | 3.4 | 12.5 |
| JDF4A | 115 | 0.88 | 3/4 | 1.5 | 8 | 64 |
| JDF4A | 230 | 0.88 | 3/4 | 1.5 | 4 | 16 |